

One-Click Cleaner Tool 1.25mm and 2.5mm Fiber Optic Cleaning Pen 800+ Cleans Fiber Optic Cleaner PRO Version — 2.5mm SC / FC / ST (Single Pen)

Fiber Optics / Fiber Optic Tools

One-Click PRO dry cleaner for 2.5 mm ferrules and SC / FC / ST connectors. Offers more than 800 nominal operations, a cleaning head with 180° rotation and manual push operation with an audible click. Antistatic resin body with textured grip area and a protective cap attached to the body.



LIMPIADOR ONE-CLICK DE FIBRA ÓPTICA

SC / FC / ST de 2,5 mm · Más de 800 limpiezas

KG-FT-CLN-2.5 PRO

Brand
KONGIA

Series
One-Click Cleaner PRO

Type
Manual fiber optic end-face cleaner

Key features

- PRO version for 2.5 mm ferrules: SC / FC / ST.
- More than 800 nominal operations per pen.
- Dry cleaning with internal tape, without adding alcohol.
- Cleaning head with 180° rotation and audible click.
- Antistatic resin body with textured grip.
- Extendable tip and window to check tape condition.
- Transparent protective cap attached to the body.
- Suitable for compatible connectors and ports, depending on the guide used.

Technical specifications

Parameter	Specification
Brand	KONGIA

Technical specifications

Parameter	Specification
Series	One-Click Cleaner PRO
SKU	KG-FT-CLN-2.5 PRO
Type	Manual fiber optic end-face cleaner
Ferrule	2.5 mm
Connectors	SC / FC / ST
Additional reference compatibility	E2000; check guide access
Application	Connector end faces and compatible adapter ports
Nominal capacity	More than 800 operations per unit
Method	Dry cleaning with internal tape
Operation	Manual push operation
Cleaning system	180° rotation
Actuation confirmation	Audible click
Body material	Antistatic resin
Grip	Textured surface
Access	Extendable tip
Monitoring	Window to check the tape
Protection	Transparent cap with flexible tether
Color	White with green head
Reference dimensions	175 × 18 × 18 mm
Power Supply	No batteries required
Sales unit	1 pen
Use	Fiber optic installation and maintenance

Applications

Optical panel maintenance

Cleaning of compatible connectors and ports in fiber distribution frames.

FTTH installations

End-face preparation before connecting patch cords and equipment.

Testing and commissioning

Inspection and cleaning before optical measurements.

Optical equipment replacement

Clean compatible connections when changing equipment or patch cords to avoid transferring contamination to new ports.

Packaging & contents

1 PRO cleaning pen with transparent protective cap and flexible tether, in an individual box. Connectors, cables and inspection equipment not included.