

Upgraded Pro Digital Network Cable Tracker · Zero Interference · PoE Burnout Protection · Adjustable Volume

Professional Installations / Network Tools

Upgraded Pro version with digital signaling, interference-free tracing, PoE burnout protection and adjustable volume. Trace network and telephone cables, verify wire order and check for open or short circuits. Price is for the complete kit.



RASTREADOR DIGITAL DE RED

Pro · Sin interferencias · Protección PoE

Volumen ajustable · RJ45 / RJ11 · 3 años

KG-NT-WT-100 Pro

KG-NT-WT-100 Pro

Type

Digital network cable tracker, upgraded Pro version

Tracing

Interference-free digital signal

PoE protection

Burnout protection; protection voltage up to 60 V

Key features

- Upgraded Pro version with digital signaling
- Interference-free tracing without background noise
- PoE burnout protection
- Receiver volume adjusted with the side control
- Network and telephone cable tracing via RJ45 / RJ11
- 1-8 and G wire sequence verification
- Continuity, open-circuit and short-circuit checks
- 3.5 mm headphone output and flashlight
- Up to 3 km tracing distance on a compatible line
- Two 9 V batteries, one per unit
- Housing and labels customizable with KONGIA branding
- 3-year KONGIA warranty

Technical specifications

Parameter	Specification
Type	Digital network cable tracker, upgraded Pro version
Tracing	Interference-free digital signal

Technical specifications

Parameter	Specification
PoE protection	Burnout protection; protection voltage up to 60 V
Maximum distance	Up to 3 km of compatible line length
Ports	RJ45, RJ11 and alligator-clip connection
Functions	Tracing, continuity, open/short circuits and 1-8 + G wire sequence
Volume	Adjustable with the receiver side control
Headphone output	3.5 mm
Power	Two 9 V batteries, one for the transmitter and one for the receiver
Transmitter maximum current	≤10 mA
Receiver maximum current	≤30 mA
Signal output	8 Vp-p
Transmitter dimensions	126 × 49 × 34 mm
Receiver dimensions	175 × 42 × 27 mm
Transmitter weight	60 g
Receiver weight	72 g
Housing	ABS plastic; KONGIA orange
Labels	Navy with KONGIA branding
Sales unit	Complete kit, accessories included
Warranty	3 years

Applications

Rack and patch-panel identification

Locate the correct end of a network cable among multiple runs.

Telephone maintenance

Identify compatible lines via RJ11 and check continuity.

Pre-commissioning verification

Check the 1-8 and G wire sequence and locate open or short circuits.

Work in noisy environments

Adjust receiver volume and use headphones when needed.

Packaging & contents

Price is for the complete kit, including all listed accessories. Contents: Transmitter ×1; receiver ×1; user manual ×1; alligator-clip cable ×1; RJ11 adapter cable ×1; RJ45 adapter cable ×1; storage box ×1; packaging box ×1; earphones ×1; 9 V batteries ×2.

Warranty

KONGIA 3-year warranty.